

Rec'd PCT/PTO 14 JUL 2004

10/501374

NO 2 / 0 5 7 1 9



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets 23 DEC 2002

REC'D 14 JAN 2003

WIPO

PCT

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

02075130.1

**PRIORITY
DOCUMENT**

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

R C van Dijk

DEN HAAG, DEN
THE HAGUE,
LA HAYE, LE

25/11/02



**Europäisches
Patentamt**

**European
Patent Office**

**Office européen
des brevets**

**Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation**

Anmeldung Nr.:
Application no.: 02075130.1
Demande n°:

Anmeldetag:
Date of filing: 15/01/02
Date de dépôt:

Anmelder:
Applicant(s):
Demandeur(s):
Koninklijke Philips Electronics N.V.
5621 BA Eindhoven
NETHERLANDS

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:
Device and method for operating a discharge lamp

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:

/

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing:
Etats contractants désignés lors du dépôt:

AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE/TR

Bemerkungen:
Remarks:
Remarques:

Device and method for operating a discharge lamp

EPO - DG 1

15. 01. 2002

(54)

The present invention relates to a device and method for operating a high-pressure discharge lamp.

High intensity discharge (HID) lamps are operated during the steady state operation within a small power urange to extend lamp life. Furthermore, during run-up operation the run-up current, i.e. the current directly after ignition, must satisfy strict conditions. The run-up current should be sufficient to allow a quick run-up, but not too large to damage the lamp.

In the drive circuitry for driving the lamp or ballast circuit, the power level during steady state and the current level during the run-up phase must be controlled. More specifically, in steady state the power supplied to the lamp should be kept in a narrow power band, independent of the lamp voltage (within the normal lamp specifications) and also the run-up current must be limited to fulfil the given lamp specifications.

Typically the ballast circuit for driving the lamp comprises a switched-mode power supply (SMPS) connected between the mains and the lamp. As HID lamps are susceptible to acoustic resonance at high frequencies, HID lamps are to be driven at relatively low frequency (typically 100 Hz) in a square wave current operation.

In a three stage drive circuit design the switched-mode power supply for HID-applications comprises a first stage including a preconditioner, for example a double rectifier for rectifying the mains (230 V 50 Hz), combined with an up converter. The second stage comprises a down converter (DC-DC converter), also called a forward or buck converter, for stabilizing the output current. The third stage of the ballast circuit comprises a commutator half- or full bridge (and ignitor) to implement the square wave current operation. The above mentioned power control during steady state and current control during run-up phase is implemented with a feedback loop. The actual output power level of the downconverter can be determined by means of measuring the input current of the downconverter. A control circuit is provided for controlling the output of the down converter. Assuming the input voltage is constant, the input current of the down converter is linearly related to the input power. Assuming further that the losses in the down converter are constant, the control circuit is able to control the output power of the down converter, based on the measured input

current. Consequently, the output current level during steady state is controlled by measuring the input current of the downconverter and providing the measured input current to the control circuit. This type of control, in case of critical discontinuous mode of operation, is called the I_{peak} control. For low lamp voltages, which indicate the run-up phase, the output current of the downconverter instead of the output power is to be controlled and is set at a fixed value as specified for the particular type of lamp used. More specifically, the output current is limited, i.e. the maximum downconverter current is set to the run-up current. For low lamp voltages the constant power feedback saturates and the current is limited.

A drawback of the above feedback control is that it can be too slow to sufficiently stabilize the lamp ballast interaction. For certain lamp types and for lamps operated on reduced power levels (dimmed lamps) the operating device can become instable and the lamp may extinguish. For other, less critical lamp types the operation may be stable to a certain degree. However, the performance of the operating device may be rather poor due to for example overshoot-effects after commutation. One of the reasons is that the sensed input current must be filtered to eliminate disturbances of the control loop caused by the switching process. A further drawback is that the feed back control can become instable. The feedback control further requires relatively complex circuitry.

In a further simplified two-stage ballast design the down converter and commutator bridge are replaced by a half-bridge commutating forward (HBCF) or a full-bridge commutating forward (FBCF) topology. In this topology, however, it is difficult or complicated to measure the peak current, especially in the HBCF topology, necessary to implement a control of the peak current (I_{peak} control).

It is therefore an object of the present invention to provide a switched mode power supply for high intensity discharge lamps wherein the lamp power during steady state and lamp current during run-up phase can be controlled and wherein the above mentioned drawbacks are obviated.

This object is achieved according to the invention in a device for operating a high-pressure discharge lamp, comprising:

a switched mode power supply circuit for supplying power or current to the high pressure discharge lamp from a supply voltage, the power supply circuit comprising at least one power switching element;

control means for controlling the at least one power switching element in its switched-on and switched-off states for controlling the power or current supplied to the high-pressure discharge lamp;

wherein the control means are adapted to control the power consumed by the lamp during its steady phase or the current consumed by the lamp during its run-up phase by controlling the on-time (T_{on}) of the switched-on state of the at least one power switching element. Forward control without any feedback or measurement by means of controlling the on-time (T_{on}) of the switched mode power supply provides a stable and simple control circuit. Also the speed of the control corresponds with the switching frequency of the switched mode power supply and consequently is larger than the control speed in case of using a standard feedback control. Typically a standard, high speed feedback control provides a control speed of about 1 kHz or less. The control speed according to the invention is equal to the switching frequency of the switched mode power supply and is typically at least 100 kHz.

Preferably the value of the on-time (T_{on}) of the at least one power switching element is a preset value, the preset value depending on the specifications of the type of discharge lamp used. During steady phase, each discharge lamp type is to be driven in a relatively narrow power band which is characteristic for the lamp type. Moreover, the lamp is to be driven in this power band substantially independent of changes in the lamp voltage. For each discharge lamp type the reference power at which the lamp is to be driven is known. Consequently, the on-time (T_{on}) if the power switching element(s) is preset such that the lamp is driven at the specified reference power.

In case of lamps with a relatively small variation in lamp voltage during life or in case of lamps which are less susceptible to variations, the on-time (T_{on}) of the at least one power switching element for a specific discharge lamp type is preferably substantially constant during operation of the lamp. Therefore a relatively simple circuit design will be sufficient.

However, in case of critical lamps, lamps with a relatively large variation in lamp voltage during life, or lamps which require an exact power level for good color properties, and/or in case the ballast is provided with the option of dimming the lamp, the power control is preferably extended with a relatively slow feedback control to guarantee a constant wattage over a broad range. This low-speed feedback uses the input current of the down converter, HBCF- or FBCF-topology as input for the feedback loop. This feedback loop guarantees a correct power level over a broad voltage range. More specifically, in a further preferred embodiment of the invention the device comprises:

- input current determining means for determining the input current of the power supply, the input current determining means providing a signal representative of the determined input current;

- a feedback means through which said signal is fed back to the control means, wherein the control means are adapted to control the on-time (T_{on}) of the at least one switching element as function of said fed back signal

Furthermore, to improve the behavior of the power control in case of application of HBCF- or FBCF-topologies wherein the depolarization process of the output capacitor may cause unwanted high peak currents during commutation, a relatively simple high-speed feedback control is preferably added. This high-speed feedback uses the lamp voltage as input for the feedback loop. More specifically, in a further preferred embodiment of the invention the device comprises:

- voltage determining means for determining the lamp voltage, the voltage determining means providing a signal representative of the determined lamp voltage,

- a feedback means through which said signal is fed back to the control means; wherein the control means are adapted to control the on-time (T_{on}) of the at least one power switching element as function of said fed back signal. The iteration frequency of the additional fast feedback control is equal to or slightly less than the switching frequency of the switched mode power supply.

The control means may comprise an additional power controller which processes the fed back signal and operates a separate controller means for controlling the T_{on} -time of the power switching element(s). Both controllers also may be combined.

In another preferred embodiment the device comprises dim level means for setting of a reduced lamp power level, the dim level means providing a signal representative of the dim level of the lamp, wherein the control means are adapted to control the on-time (T_{on}) of the at least one power switching element as function of said signal. The control means may comprise an additional power controller which processes the dim signal and operates a separate controller for controlling the T_{on} -time of the power switching element(s). The simple fast respectively slow feedback controller for precise power adjustments, the T_{on} time controller and/or possibly the additional dim level controller may also be combined onto one single device.

The additional controller may be implemented in a low-performance microprocessor, because the speed of the A/D-converters is not critical for the relatively slow average power adjustments.

The iteration frequency of the additional slow feedback control is 100 Hz or less, preferably about 10 Hz or less. Since the on-time (T_{on}) can be iteratively adapted with a iteration frequency far lower than the switching frequency of the switched mode power

supply, the fast power disturbances are controlled by the T_{on} -forward control, while the slow power disturbances are controlled by the additional feedback circuit.

According to another aspect of the invention a method is provided for operating a high-pressure discharge lamp, comprising:

5 supplying power to the high pressure discharge lamp from a supply voltage, using at least one power switching element;

controlling the power consumed by the lamp during its steady phase using control means;

wherein said the control means control the lamp power during the steady state of the lamp by
10 fixing the on-time (T_{on}) the at least one power switching element.

Preferably the method comprises also the steps of presetting the value of the on-time (T_{on}) of the at least one power switching element depending on the specifications of the type of discharge lamp used.

15

Further advantages, features and details of the present invention will be elucidated with reference to the annexed drawings, in which:

Fig. 1 shows a schematic diagram of a lamp and its ballast circuit for driving the lamp;

20

Fig. 2 shows a schematic circuit diagram of a half-bridge commutating forward (HBCF) topology of a switched mode power supply;

Fig. 3 shows a graph of the current (I) supplied by the switched mode power supply, as function of the time (t) in case the switched mode power supply is operated in a critical discontinuous mode;

25

Fig. 4 shows a graph of the lamp power (P_{lamp}) and lamp current (I_{lamp}) during the run-up phase and the steady phase, as function of the lamp voltage (U_{lamp});

Fig. 5 shows a graph of the lamp current (I_{lamp}) as function of the lamp voltage (U_{lamp}) for constant I_{peak} -control and for constant T_{on} -control;

30 Fig. 6 shows a graph of the lamp power (P_{lamp}) as function of the lamp voltage (U_{lamp}) for constant I_{peak} -control and for constant T_{on} -control;

Fig. 7a shows a schematic diagram of the power controller without feedback;

Fig. 7b shows a schematic diagram of an additional feedback power controller of a further preferred embodiment; and

Fig. 8 shows a circuit diagram of a power controller with combined feedback and T_{on} controller, including an optional dim level input switch.

5 Figure 1 shows a three-stage ballast for a high discharge lamp L comprising a preconditioner 1, which includes a rectifier 2 for converting the AC supply voltage (typically a 230 V 50 HZ mains) to a DC supply voltage and an up-converter 3. The ballast furthermore comprises an energy buffer 4, a down-converter 5 and a full bridge commutator 6 for driving the lamp L in a square wave operation. The full bridge commutator 6 comprises four
10 MOSFETS 7, a series igniter inductor 8 or an igniter transformer 8, a lamp capacitor 9 and a separate ignitor circuit 10 for driving the lamp in the ignition phase. The preconditioner 1, down converter 5 and commutator 6 are controlled by a control circuit 11.

In broken lines is shown the prior feedback control loop. The input current I_{sense} of the down converter 5 is measured and fed back to the control circuit 11. Based on
15 the measured input current I_{sense} , the control circuit 11 controls the down converter so as to set the output power (steady state) or output current (run-up state) of the down converter 5 to the desired level.

In figure 2 is shown the end part of a two-stage ballast for a high discharge lamp. In the two-stage ballast the circuitry of the last two stages of the three stage ballast are
20 combined. Compared to the three-stage ballast the two-stage ballast is simple and the costs for manufacturing are relatively low. The half bridge commutating forward (HBCF) circuit of figure 2 shows a first MOSFET T1, a second MOSFET T2, a first and a second diode D1 and D2, a lamp inductor 8, a lamp capacitor 9, the lamp L and two capacitors C_s . Instead of a half bridge a full bridge is conceivable, wherein the capacitors C_s are replaced by MOSFETS.
25 The half bridge commutating forward circuit or full bridge commutating forward circuit is operated in the critical discontinuous mode to allow zero voltage switching. Each half commutation period (commutation frequency in the order of 100 Hz), one MOSFET (T1 or T2) is operated in combination with the diode (D2 or D1) of the other MOSFET.

The average level of the output current of the three-stage down converter
30 circuit or the two-stage half/full bridge commutating forward circuit (FBCF/HBCF) when operated in the discontinuous mode, is determined by the minimum and maximum level of the current or the time T_{on} during which the MOSFETS of the circuit is active (switched-on state). When operated in the critical discontinuous mode, wherein the minimum current level

is zero, however, the level of the output current can be determined by the T_{on} -time or the maximum current value I_{peak} only, as is shown in figure 3.

In table I are shown the equations valid for I_{peak} control which is implemented in the earlier-mentioned feedback control. The constant current I_{peak} control is further elucidated in figure 5 and 6, wherein the lamp current I_{lamp} and the lamp power P_{lamp} as function of the lamp voltage U_{lamp} is shown.

	I_{peak} control	T_{on} control
$I_{L,peak}$	$I_{L,peak} = \text{constant}$	$I_{L, peak} = \frac{(U_{sup ply} - U_{lamp}) \cdot T_{on}}{L}$ $T_{on} = \text{constant}$
I_{lamp}	$I_{lamp} = \frac{I_{L,peak}}{2} = \text{constant}$	$I_{lamp} = \frac{(U_{supply} - U_{lamp}) \cdot T_{on}}{2L}$ $T_{on} = \text{constant}$
P_{lamp}	$P_{lamp} = U_{lamp} \cdot I_{lamp}$ $I_{lamp} = \text{constant}$	$P_{lamp} = (U_{supply} \cdot U_{lamp} - U_{lamp}^2) \left(\frac{T_{on}}{2L} \right)$ $\frac{T_{on}}{2L} = \text{constant}$

Table I Lamp power and lamp current equations for constant T_{on} control and constant I_{peak} control

In the run-up phase, which is shown in the left part of figure 4, the lamp voltage is relatively low (typically 20 V) and the lamp current level I_{lamp} is maintained constant at a reduced level. The level is dependent on the specifications of the particular lamp in use. The theoretical power curve in the run-up phase shows a diagonal line. This is true for a short time scale. During steady state, shown in the right part of this figure, the power level instead of the current level is to be kept constant. Hence, for higher voltages the feedback control loop comes into action and stabilizes the power to a constant level, independent of the lamp voltage. The feedback loop will provide a constant power line over a broad lamp voltage range in steady state.

In case of using a feedback loop, the output current value is adapted during steady state by the feedback control circuit 11 to such an extent that a constant power level is maintained. If, for example, the lamp voltage changes from 100 V to about 115 V, the lamp

power would rise from 80 W (a) to 92 W (b). To avoid this and therefore to keep the power level P_{lamp} constant, the feedback control reduces the output lamp current from 0,8 A to 0,7 A (arrow P_1 in figure 5). This results in a reduction of the power level (arrow P_2 in figure 6) so as to keep the power level P_{lamp} constant. In this figures the continuous thin line and the broken thin line represent the lamp current and lamp power values in case of a constant I_{peak} control, before (orig) respectively after (reduc) the feedback control intervenes.

In the feedback loop the switching behavior must be filtered out to avoid instabilities in the closed loop. This slows down the response time constant to several times below the switching frequency.

10 In the constant T_{on} control according to the invention, the equations valid in the critical discontinuous mode are given in the right-hand side of table I. The constant T_{on} control is further elucidated by the thick lines shown in figures 5 and 6.

In case the control circuitry 11 controls the time during which the switched mode power supply is in the switched on and/or the switched off state (T_{on} -control), the lamp power curve shows a parabolic shape, as clearly is shown in figure 6, the power curve being the same on a short time scale as in steady state. The T_{on} -time of the power supply is preset by the control circuitry 11 to a value wherein the voltage supplied to the lamp corresponds to the nominal or reference lamp voltage, for example a reference lamp voltage of 100 V (point a). As shown in figure 6, the power level for a preset T_{on} -time is substantially constant within a considerable wide voltage range. The present generation of high discharge lamps typically shows a 5% variation in nominal lamp power at the most. However, even in case of a 15% variation of the lamp voltage (for example a 15% increase from 100 V to 115 V), such as due to a voltage peak as a result of re-ignition of the lamp, this only results in a relatively small reduction of the lamp power P_{lamp} (point d). Consequently, in the voltage range from 100 to 115 V the lamp power is more or less constant. The reduction is less than 5% (P_3), which in practical applications is acceptable. Although the power is not exactly constant as function of the voltage, it is acceptable flat within a reduced lamp voltage range.

For very large variations, for example for very high lamp voltages, the power level is furthermore automatically reduced, which results in good end of life behavior and reduces end of life problems.

The above description of the constant T_{on} -time control shows that, with a fixed input voltage of the switched mode power supply, the desired output can be attained and feedback circuitry, that must be applied in the constant I_{peak} control, can be omitted.

Furthermore, the use of a fixed forward control with a fixed setting gives a stable lamp power

control and run-up current control, and provides a fast response, i.e. a response substantially equal to the switching frequency (100 kHz) of the commutator, which enables transients to be followed. Additionally a relatively simple circuit design will suffice.

In the above embodiment the T_{on} -time is kept constant to achieve a
5 substantially constant lamp power level or reference power level. In applications wherein a user is given the opportunity to dim the lamp power level or when critical lamps or lamps showing a large variation in lamp voltage during life are applied, the "feed forward" control according to a further preferred embodiment is extended with a relatively slow feedback control. This additional feedback control enables the preset T_{on} -time of the power supply to
10 be reduced in order to dim the lamp power to a desired dimmed power level or guarantees a more constant lamp power over a broad voltage range in case of critical lamps.

Furthermore, also in case of a two-stage power supply using HBCF- or FBCF-topology, according to a preferred embodiment, an additional, relatively fast feedback may be needed. Direct after commutation, i.e. after every current reversal, very high current peaks
15 flow through the inductor which is caused by the depolarization process of the output capacitor. Also the current must be reduced in the run-up phase and in a short circuit situation. Therefore, to avoid saturation of the HBCF-/FBCF-coil, the T_{on} -time should be reduced for low lamp voltage.

Figure 7a is a schematical representation of the T_{on} power or current control
20 without using any additional feedback, as explained above. Figure 7b is a schematical representation of the T_{on} power or current control wherein an additional feedback is applied.

The additional control loop can be implemented in a low performance microprocessor system because the speed of the A/D-converters is not critical for the slow average power adjustment. The fast power disturbances are controlled by means of the earlier
25 described T_{on} forward control part.

Furthermore, figure 8 shows a diagram of a lamp and its ballast circuitry in a further embodiment, wherein the option of dimming of the lamp is provided. When the lamp power level is to be reduced from a fixed reference power level to a user set dimmed power level, the user operates an input control (not shown), which sends (A) a signal representative
30 of the dim level to the additional power controller. The additional power controller then controls the T_{on} controller (A) so as to indirectly control the T_{on} time (B) of the power circuit (figure 7b) or reduces the T_{on} time of the power circuit directly (figure 8), i.e. the down converter circuit or the half/full bridge commutating forward (FBCF/HBCF), accordingly.

In case of lamps showing a large variation in lamp voltage, a relatively slow power feedback loop is used to guarantee a correct power level over a broad voltage range. In this feedback loop (figure 8) the measured input current is fed back.

5 In case of a HBCF- or FBCF-topology an additional high speed feedback loop may be implemented, as mentioned earlier. In this feedback loop the lamp voltage is measured, preferably indirectly to avoid differential lamp voltage measurement. In figure 7b line C represents a lamp related signal such as the lamp voltage, which signal is fed back to the power controller. The additional power control circuitry uses this signal to have the T_{on} controller reduce the T_{on} time of the power circuit, which shifts the power curve over the
----- 10 ----- lamp voltage axis accordingly.

The present invention is not limited to the above described preferred embodiment thereof; the rights sought are defined by the following claims, within the scope of which many modifications can be envisaged.

CLAIMS:

15. 01. 2002

(54)

1. Device for operating a high-pressure discharge lamp, comprising:
a switched mode power supply circuit for supplying power to the high pressure discharge lamp from a supply voltage, the power supply circuit comprising at least one power switching element;

5 control means for controlling the at least one power switching element in its switched-on and switched-off states for controlling the power or current supplied to the high-pressure discharge lamp;

wherein the control means are adapted to control the power consumed by the lamp during its steady phase or the current consumed by the lamp during its run-up phase by controlling the on-time (T_{on}) of the switched-on state of the at least one power switching element.

2. Device according to claim 1, wherein the value of the on-time (T_{on}) of the at least one power switching element is preset value, the preset value depending on the specifications of the type of discharge lamp used.

3. Device according to claim 1 or 2, wherein the on-time (T_{on}) of the at least one power switching element for a specific discharge lamp type is substantially constant.

4. Device according to any of the preceding claims, comprising:

- input current determining means for determining the input current of the power supply, the input current determining means providing a signal representative of the determined input current;

- a feedback means through which said signal is fed back to the control means, wherein the control means are adapted to control the on-time (T_{on}) of the at least one switching element as function of said fed back signal.

5. Device according to any of the preceding claims, comprising

- voltage determining means for determining the lamp voltage, the voltage determining means providing a signal representative of the determined lamp voltage,

- a feedback means through which said signal is fed back to the control means; wherein the control means are adapted to control the on-time (T_{on}) of the at least one power switching element as function of said fed back signal.

- 5 6. Device according to any of the preceding claims, comprising a dim level means for setting of a reduced lamp power level, the dim level means providing a signal representative of the dim level of the lamp, wherein the control means are adapted to control the on-time (T_{on}) of the at least one power switching element as function of said signal.
- 10 7. Device according to claim 5 or 6, wherein the control means comprise a feedback controller for controlling the control means.
- 15 8. Device according to claim 7, wherein the control means are adapted to provide fast lamp power adjustments and the feedback controller is adapted to provide relatively slow lamp power adjustments.
- 20 9. Device according to any of claims 4-8, wherein the on-time (T_{on}) is iteratively adapted with a iteration frequency lower than the switching frequency of the switched mode power supply.
10. Device according to any of the preceding claims, wherein the switching frequency of the switched mode power supply is at least 100 kHz.
- 25 11. Device according to claim 9, wherein the iteration frequency is 100 Hz or less, preferably about 10 Hz or less.
- 30 12. Device according to any of the preceding claims, wherein use is made of a half or full-bridge power supply and a filter circuit comprising a series inductor (L) and at least one filter capacitor (C) parallel to the lamp.
13. Device according to any of the preceding claims, wherein the switched mode power supply comprises a half-bridge or full-bridge commutating forward topology.
-

14. Device according to any of the claims 1-13, wherein the switch mode power supply comprises a down converter

15. Method for operating a high-pressure discharge lamp, comprising:

5 supplying power to the high pressure discharge lamp from a supply voltage, using at least one power switching element;

controlling the power consumed by the lamp during its steady phase using control means;

10 wherein said the control means control the lamp power during the steady state of the lamp by fixing the on-time (T_{on}) the at least one power switching element.

16. Method according to claim 15, comprising presetting the value of the on-time (T_{on}) of the at least one power switching element depending on the specifications of the type of discharge lamp used.

15 17. Method according to any of the claims 15-16, wherein the on-time (T_{on}) of the at least one power switching element is kept substantially constant.

20 18. Method according to any of the claims 15-17, comprising determining the lamp voltage, providing a signal representative of the determined lamp voltage, feeding said signal back to the control means and adapting the on-time (T_{on}) of the at least one power switching element as function of the determined lamp voltage.

ABSTRACT:

The invention relates to a device for operating a high-pressure discharge lamp, comprising:

a switched mode power supply circuit for supplying power to the high pressure discharge lamp from a supply voltage, the power supply circuit comprising at least
5 one power switching element, and

control means for controlling the at least one power switching element in its switched-on and switched-off states for controlling the power or current supplied to the high-pressure discharge lamp.

According to the invention the control means are adapted to control the power
10 consumed by the lamp during its steady phase or the current consumed by the lamp during its run-up phase by controlling the on-time (T_{on}) of the switched-on state of the at least one power switching element.

Fig. 1

EPO - DG 1
15. 01. 2002

(54)

1/4




FIG. 1




FIG. 2




FIG. 3

EPO - DG 1

15. 01. 2002

(54)

2/4




FIG. 4




FIG. 5

3/4




FIG. 6




FIG. 8




FIG. 7A




FIG. 7B

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.